



フック棒

The figure consists of three technical drawings illustrating the installation details of the 'S' series fire alarm pull station for different mounting surfaces. Each drawing includes dimensions in millimeters and labels for components like 'タッピングビス' (tapping screw) and '取付金具' (mounting bracket).

- 壁面取付詳細 S=1/5 (Wall Mounting Detail S=1/5):** This drawing shows the pull station mounted on a wall. Key dimensions include a total width of 85.4 mm, a mounting bracket width of 9.9 mm, and a distance of 28.5 mm from the wall to the center of the device. The device has a height of 88 mm and a mounting hole diameter of 4.7 mm. A tapping screw is shown securing the bracket to the wall. A '映写光' (projection light) arrow points to the bottom of the device.
- 天井直取付詳細 S=1/5 (Ceiling Direct Mounting Detail S=1/5):** This drawing shows the pull station mounted directly on a ceiling. Key dimensions include a total width of 108.5 mm, a mounting bracket width of 28.5 mm, and a distance of 55 mm from the ceiling to the center of the device. The device has a height of 88 mm and a mounting hole diameter of 4.7 mm. Two tapping screws are shown securing the bracket to the ceiling. A '映写光' (projection light) arrow points to the bottom of the device.
- ボックス取付詳細 S=1/5 (Box Mounting Detail S=1/5):** This drawing shows the pull station mounted inside a box. Key dimensions include a total width of 150 mm, a mounting bracket width of 75 mm, and a distance of 20 mm from the box wall to the center of the device. The device has a height of 88 mm and a mounting hole diameter of 4.7 mm. Two tapping screws are shown securing the bracket to the box wall. A '映写光' (projection light) arrow points to the bottom of the device.

生 地	スーパーホワイト マット 防炎品	付属品	取付金具・取付金具用型紙・取付金具ビス一式		
ケ ー ス	材質：アルミ型材 オフホワイト色		取付金具固定用タッピングビス（M4×40-8本）、フック棒		
		オプション			
質 量	約 11. kg	別途工事	スクリーンボックス（150×150×3000以上）		
泉 株式会社 IZUMI-COSMO CO.,LTD.		尺度 1/30 1/5	品名 天吊・壁付けタイプ120型ワイド(16:9) スプリング巻上スクリーン(全白)		
		単位 mm	Rev.	型番 IS-S120HDAW	No.